

PXR-62ESL Reader

Features



(SG)



(DG)

- Supports 125 KHz-EM card.
- Reading distances are around 8-10 cm.
- Provides RS-485 communication interface for long distance installation
- The ability to automatically detect the connection status with the control panel. While disconnecting from control panel, it can still work properly by auto learning mode
- Auto-Learning function. 470 temporary cards' capacity under standalone operation mode for emergent door open.
- Wide range of operating temperature to meet the requirements of tropical or frigid zone climate environment.
- Case sensor detection function.
- Watchdog function secures system free from halting.


Ordering Information

Package Content:

- PXR-62 x 1
- Quick Start Guide x 1
- Accessory Pack x 1

Model No. Identification

PXR-62ESL



Color



Specifications

Model No.	PXR-62ESL
Read Format	EM (125 KHz)
Read Range	8-10 cm(max)
Comm. Interface	RS-485
Input Ports	3 Sensors (Door Sensor x 1 、 Exit Button x 1 、 Case Sensor x 1)
Output Ports(Built-in)	Relay x 1 (Door Lock)
Output Ports(External)	O.C. Output x 2 (Door Lock / Alarm, external ACU-30/90)
ID Setting	DIP switch setting
Comm. Baudrate	19,200 bps-N-8-1
LED Indicator	Power / Comm.
Beep Tone	Buzzer
Power Input	DC 12V / 1A
Current Consumption	200mA (max)
Operating Temp.	-10°C~ 70°C / 14°F~ 158°F
Relative Humidity	20% ~ 80%(Non-condensing)
Dimensions (LxWxH)(mm)	120 x 76 x 27